

Mini6045 PIN 脚定义

发布: 2010-04-14

www.timll.com



版本更新记录

版本	发布日期	描述
1.0	2010-04-14	初始发布

访问如下地址，可获取更多信息：<http://www.timll.com>

Mini6045 工业级核心板 PIN 脚定义

Pin(J8)	Signal	Pin(J8)	Signal	Pin(J6)	Signal	Pin(J6)	Signal
1	GND	41	GND	1	GND	41	SHDN
2	TA-	42	TA+	2	1V8	42	PC1
3	TB-	43	TB+	3	PC0	43	PC6
4	TC-	44	TC+	4	PC7	44	PC9
5	TD-	45	TD+	5	PC10	45	PC11
6	TCLK-	46	TCLK+	6	PC12	46	PC13
7	GND	47	VDD33	7	PC15	47	PC16
8	PD24	48	PD25	8	PC17	48	PC18
9	PD26	49	PD27	9	PC19	49	PC20
10	PA6	50	PE31	10	DRRXD	50	DRTXD
11	PA8	51	PA7	11	PC21	51	PC22
12	PA20	52	PA9	12	PC23	52	PC24
13	PA22	53	PA21	13	PC25	53	PC26
14	PA24	54	PA23	14	PC27	54	PC28
15	PD20	55	PD22	15	PC29	55	PC30
16	PD21	56	PD23	16	PC31	56	PD0
17	PA28	57	PA27	17	PD6	57	PD7
18	PA30	58	PA29	18	PD8	58	PD9
19	PB0	59	PA31	19	GND	59	PD11
20	PB2	60	PB1	20	GND	60	WKUP
21	PB5	61	PB4	21	PD12	61	PD13
22	PB7	62	PB6	22	PD14	62	PD15
23	PB9	63	PB8	23	PD16	63	PD17
24	PB11	64	PB10	24	PD18	64	PD19
25	PA26	65	PA25	25	PD29	65	PD28
26		66	GND	26	PD31	66	PD30
27	PB15	67	PB14	27	PB20	67	PB21
28	PB17	68	PB16	28	PB22	68	PB23
29	PB19	69	PB18	29	PB24	69	PB25
30	NRST	70	VDD5V	30	PB26	70	PB27
31	PD10	71	VSBAT	31	PB28	71	PB29
32	PA5	72	PA4	32	PB30	72	NTRST
33	PA2	73	PA1	33	PB31	73	TDI
34	PA3	74	PA0	34	RTCK	74	TDO
35	GND	75	PB3	35	TCK	75	TMS
36	LED4	76	LED5	36	USB_B_VB	76	USB_A_VB

37	RX2-	77	RX2+	37	HDPA	77	HDMA
38	VDD33	78	AVDDT	38	VDD5V	78	
39	TX2-	79	TX2+	39	HDPB	79	HDMB
40	GND	80	VDD5V	40	GND	80	GND

联系我们



An Embest Company

深圳市天漠科技有限公司

地址：深圳市罗湖区太宁路 85 号罗湖科技大厦 405 室 邮编：518020

电话：0755-25631357 25636285 25500944

传真：0755-25616057

技术支持电话：0755-25503401

销售 E-Mail: sales@timll.com

技术支持 E-Mail: Support@timll.com

网址: www.timll.com www.armkits.com

www.timll.com